

Buzzers

Bell Buzzer

730 Series

Edwards 730 Dixie Buzabel™ is a non-adjustable, combination bell and buzzer with a grounded frame, suitable for use in residential, commercial and OEM applications. It may be operated using AC power supplied by a 596 transformer, or from DC power.

Features and Specifications

- Fully enclosed
- Satin aluminum finish
- Attractive snap-on covers
- Enclosed binding posts
- Enclosed terminals



Ordering Information

Description	Cat. No.	Operating Voltage ¹	Current	VA	dB at 1m/10ft.	DC Coil Res (Ohms)
Bell and Buzzer	730	6V AC	0.7 A	4.2	92/82	3
		3-6V DC	1.4 A	8	92/82	3
		6-8V AC	1.4 A	8	92/82	3

¹AC voltage frequency is 60 Hz.

Weights and Dimensions

Cat. No.	Approx. Net Weight (lb.)	Approx. Shipping Weight (lb.)
730	0.46	0.48

